

Analog Input Module (Current)

RIO3-A... User Manual



Version 1.03

REVISION HISTORY				
REV	PAGE	REMARKS	DATE	EDITOR
1.02		New Document	Nov 2020	(OPR), (PF)
1.02	52	Remove product list table and add a reference	Aug 2021	Faber
1.03	10,15,20,26,32 38	Status led edited; Specification updated	Feb 2025	Lankala
	16,27	Add Module Resolution (14bit)		

Table of Contents

1 Important Notes	6
1.1 Safety Instruction	7
1.1.1 Symbols	7
1.1.2 Safety Notes	7
1.1.3 Certification.....	7
2 Analog Input Module List.....	8
3 Specification.....	9
3.1 RIO3-AX4I	9
3.1.1 Wiring Diagram.....	9
3.1.2 LED Indicator.....	10
3.1.3 Channel Status LED.....	10
3.1.4 Environment Specification	10
3.1.5 Specification	11
3.1.6 Data Value / Current.....	12
3.1.7 Mapping Data into the Image Table.....	13
3.1.8 Parameter Data	13
3.2 RIO3-AXH4I.....	14
3.2.1 Wiring Diagram.....	14
3.2.2 LED Indicator.....	15
3.2.3 Channel Status LED.....	15
3.2.4 Environment Specification	15
3.2.5 Specification	16
3.2.6 Data Value / Current.....	17
3.2.7 Mapping Data into the Image Table.....	18
3.2.8 Parameter Data	18
3.3 RIO3-AX8I	19
3.3.1 Wiring Diagram.....	19
3.3.2 LED Indicator.....	20
3.3.3 Channel Status LED.....	20
3.3.4 Environment Specification	20

3.3.5 Specification	21
3.3.6 Data Value / Current	22
3.3.7 Mapping Data into the Image Table.....	23
3.3.8 Parameter Data	24
3.4 RIO3-AXH8I.....	25
3.4.1 Wiring Diagram.....	25
3.4.2 LED Indicator.....	26
3.4.3 Channel Status LED.....	26
3.4.4 Environment Specification	26
3.4.5 Specification	27
3.4.6 Data Value / Current	28
3.4.7 Mapping Data into the Image Table.....	29
3.4.8 Parameter Data	30
3.5 RIO3-AX16IC.....	31
3.5.1 Wiring Diagram.....	31
3.5.2 LED Indicator.....	32
3.5.3 Channel Status LED.....	32
3.5.4 Environment Specification	32
3.5.5 Specification	33
3.5.6 Data Value / Current	34
3.5.7 Mapping Data into the Image Table.....	35
3.5.8 Parameter Data	36
3.6 RIO3-AX16IT.....	37
3.6.1 Wiring Diagram.....	37
3.6.2 LED Indicator.....	38
3.6.3 Channel Status LED.....	38
3.6.4 Environment Specification	38
3.6.5 Specification	39
3.6.6. Data Value / Current	40
3.6.7. Mapping Data into the Image Table.....	41
3.6.8. Parameter Data	42
4. Dimension	43
4.1. 10-Pts. Spring Type	43

4.2.	20-Pin Connector Type.....	44
4.3.	18-Pts. Spring Type.....	45
5.	Mounting.....	46
5.1.	I/O Inserting and Removing Devices	46
5.2.	RTB (Removable Terminal Block)	47
6.	G-Bus Pin Description.....	48
	APPENDIX A	49
A.1.	Product List.....	49
A.2.	Glossary	49

1 Important Notes

Solid state equipment has operational characteristics differing from those of electromechanical equipment.

Safety Guidelines for the Application, Installation and Maintenance of Solid-State Controls describes some important differences between solid state equipment and hard-wired electromechanical devices.

Because of this difference, and because of the wide variety of uses for solid state equipment, all persons responsible for applying this equipment must satisfy themselves that each intended application of this equipment is acceptable.

In no event will HITACHI be responsible or liable for indirect or consequential damages resulting from the use or application of this equipment.

The examples and diagrams in this manual are included solely for illustrative purposes. Because of the many variables and requirements associated with any installation, HITACHI cannot assume responsibility or liability for actual use based on the examples and diagrams.

Warning!

- ✓ **If you don't follow the directions, it could cause a personal injury, damage to the equipment or explosion**
- ✓ Do not assemble the products and wire with power applied to the system. Else it may cause an electric arc, which can result into unexpected and potentially dangerous action by field devices. Arching is explosion risk in hazardous locations. Be sure that the area is non-hazardous or remove system power appropriately before assembling or wiring the modules.
- ✓ Do not touch any terminal blocks or IO modules when system is running. Else it may cause the unit to an electric shock or malfunction.
- ✓ Keep away from the strange metallic materials not related to the unit and wiring works should be controlled by the electric expert engineer. Else it may cause the unit to a fire, electric shock or malfunction

Caution!

- ✓ **If you disobey the instructions, there may be possibility of personal injury, damage to equipment or explosion. Please follow below Instructions.**
- ✓ Check the rated voltage and terminal array before wiring. Avoid the circumstances over 50°C of temperature. Avoid placing it directly in the sunlight.
- ✓ Avoid the place under circumstances over 85% of humidity.
- ✓ Do not place Modules near by the inflammable material. Else it may cause a fire.
- ✓ Do not permit any vibration approaching it directly.
- ✓ Go through module specification carefully, ensure inputs, output connections are made with the specifications. Use standard cables for wiring.
- ✓ Use Product under pollution degree 2 environment.

1.1 Safety Instruction

1.1.1 Symbols

DANGER 	Identifies information about practices or circumstances that can cause an explosion in a hazardous environment, which may lead to personal injury or death property damage, or economic loss.
IMPORTANT	Identifies information that is critical for successful application and understanding of the product.
ATTENTION 	Identifies information about practices or circumstances that can lead to personal injury, property damage, or economic loss. Attentions help you to identify a hazard, avoid a hazard, and recognize the consequences.

1.1.2 Safety Notes

DANGER 	The modules are equipped with electronic components that may be destroyed by electrostatic discharge. When handling the modules, ensure that the environment (persons, workplace and packing) is well grounded. Avoid touching conductive components, G-BUS Pin.
--	--

1.1.3 Certification

UL Listed Industrial Control Equipment, certified for U.S.

See UL File E196687

CE Certificate

EN 61000-6-2; Industrial Immunity

EN 61000-6-4; Industrial Emissions

Reach, RoHS (EU, CHINA), EAC


2 Analog Input Module List

RIO3-Number	Description	ID (hex)
RIO3-AX4I	Analog input, 4 Channels, 0~20mA, 4~20mA, 12Bits, 10RTB	3114
RIO3-AXH4I	Analog input, 4 Channels, 0~20mA, 4~20mA, 16Bits, 10RTB	3154
RIO3-AX8I	Analog input, 8 Channels, 0~20mA, 4~20mA, 12Bits, 10RTB	3118
RIO3-AXH8I	Analog input, 8 Channels, 0~20mA, 4~20mA, 16Bits, 10RTB	3158
RIO3-AX16IC	Analog input, 16 Channels, 0~20mA, 4~20mA, 12Bits, 20P Connector	311F
RIO3-AX16IT	Analog input, 16 Channels, 0~20mA, 4~20mA, 16Bits, 20P Connector	317F

3 Specification


3.1 RIO3-AX4I

3.1.1 Wiring Diagram



Pin No.	Signal Description	Signal Description	Pin No.
0	Input Channel 0	Input Channel 1	1
2	Input Channel 2	Input Channel 3	3
4	Input Channel Common (AGND)	Input Channel Common (AGND)	5
6	Input Channel Common (AGND)	Input Channel Common (AGND)	7
8	F.G	F.G	9

3.1.2 LED Indicator



LED No.	LED Function / Description	LED Color
0	Input Channel 0	Green
1	Input Channel 1	Green
2	Input Channel 2	Green
3	Input Channel 3	Green

3.1.3 Channel Status LED

Status	LED	To indicate
Normal Operation	OFF Green	< 0.5% (Maximum Input Value) > 0.5% (Maximum Input Value)
Overrun/Underrun	OFF	> 21mA (Maximum Range Over) < 3mA (Minimum Range Over, 4 ~ 20mA)
Field Power Error	All Channel Repeat the Green and Off	Field Power is unconnected

3.1.4 Environment Specification

Environmental Specification	
Operation Temperature	-40°C ~ 70°C
UL Temperature	-20°C ~ 60°C
Storage Temperature	-40°C ~ 85°C
Relative Humidity	5% ~ 90% non-condensing
Mounting	DIN Rail
General Specification	
Shock Operating	IEC 60068-2-27
Vibration Resistance	Based on IEC 60068-2-6, 4g
Industrial Emissions	EN61000-6-4/A11: 2011
Industrial Immunity	EN61000-6-2: 2005
Installation Position	Vertical and horizontal installation is possible
Product Certifications	CE, UL


3.1.5 Specification

Items	Specification
Input Specification	
Inputs Per Module	4 Channels Single Ended, Non-Isolated Between Channel
Indicators (Logic side)	4 Green Input Status
Resolution in Ranges	12 Bits: 4.88uA/Bit (0~20mA), 3.91uA/Bit (4~20mA)
Input Current Ranges	0 ~ 20mA, 4 ~ 20mA
Data Format	16 Bits Integer (2' complement)
Module Error	±0.1% Full Scale @ 25°C ambient ±0.3% Full Scale @ -40°C ~ 70°C
Input Impedance	121.5 Ω
Diagnostic	Diagnostic Field Power Off: LED Blinking Field Power On: LED Off < 0.5% (Maximum Input Value) Field Power On: LED On > 0.5% (Maximum Input Value) Maximum Range Over: LED Off > 21mA Minimum Range Over: LED Off < 3mA (4~20mA)
Conversion Time	0.7msec / All Channels
Field Calibration	Not Required
Common Type	4 Common, Field Power 0V is the Common (AGND)
General Specification	
Power Dissipation	Max. 25mA @ 5.0Vdc
Isolation	I/O to Logic: Isolation Field Power: Non-Isolation
UL Field Power	Supply Voltage: 24Vdc nominal, Class 2
Field Power	Supply Voltage: 24Vdc nominal Voltage Range: 18~30Vdc Power Dissipation: Max. 25mA @ 24Vdc
Wiring	I/O Cable Max. 2.0mm ² (AWG 14)
Torque	0.8Nm (7lb-in)
Weight	58g
Module Size	12mm x 99mm x 70mm

3.1.6 Data Value / Current


Current Range: 0 ~ 20mA

Current	0.0mA	5.0mA	10.0mA	20.0mA
Data(Hex)	H0000	H03FF	H07FF	H0FFF



Current Range: 4 ~ 20mA


Current	4.0mA	8.0mA	12.0mA	20.0mA
Data(Hex)	H0000	H03FF	H07FF	H0FFF



3.1.7 Mapping Data into the Image Table.

Input Module Data

Analog Input Ch0
Analog Input Ch1
Analog Input Ch2
Analog Input Ch3



Input Image Value

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0					Analog Input Ch0 Low byte			
Byte 1					Analog Input Ch0 High byte			
Byte 2					Analog Input Ch1 Low byte			
Byte 3					Analog Input Ch1 High byte			
Byte 4					Analog Input Ch2 Low byte			
Byte 5					Analog Input Ch2 High byte			
Byte 6					Analog Input Ch3 Low byte			
Byte 7					Analog Input Ch3 High byte			

3.1.8 Parameter Data


Valid Parameter length: 6 Bytes

Parameter Data

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0					Current Range for Channel 0 (H00: 0~20mA, H01: 4~20mA)			
Byte 1					Current Range for Channel 1 (H00: 0~20mA, H01: 4~20mA)			
Byte 2					Current Range for Channel 2 (H00: 0~20mA, H01: 4~20mA)			
Byte 3					Current Range for Channel 3 (H00: 0~20mA, H01: 4~20mA)			
Byte 4					Filter Time (H00: Default Filter(20) / H01: Fastest ~ / H3E: Slowest)			
Byte 5					Not used (=00)			


3.2 RIO3-AXH4I

3.2.1 Wiring Diagram



Pin No.	Signal Description	Signal Description	Pin No.
0	Input Channel 0	Input Channel 1	1
2	Input Channel 2	Input Channel 3	3
4	Input Channel Common (AGND)	Input Channel Common (AGND)	5
6	Input Channel Common (AGND)	Input Channel Common (AGND)	7
8	F.G	F.G	9

3.2.2 LED Indicator



LED No.	LED Function / Description	LED Color
0	Input Channel 0	Green
1	Input Channel 1	Green
2	Input Channel 2	Green
3	Input Channel 3	Green

3.2.3 Channel Status LED

Status	LED	To indicate
Normal Operation	OFF Green	< 0.5% (Maximum Input Value) > 0.5% (Maximum Input Value)
Overrun/Underrun	OFF	< 3mA (Minimum Range Over, 4 ~ 20mA)
Field Power Error	All Channel Repeat the Green and Off	Field Power is unconnected

3.2.4 Environment Specification

Environmental Specification	
Operation Temperature	-40°C ~ 70°C
UL Temperature	-20°C ~ 60°C
Storage Temperature	-40°C ~ 85°C
Relative Humidity	5% ~ 90% non-condensing
Mounting	DIN Rail
General Specification	
Shock Operating	IEC 60068-2-27
Vibration Resistance	Based on IEC 60068-2-6, 4g
Industrial Emissions	EN61000-6-4/A11: 2011
Industrial Immunity	EN61000-6-2: 2005
Installation Position	Vertical and horizontal installation is possible
Product Certifications	CE, UL


3.2.5 Specification

Items	Specification
Input Specification	
Inputs Per Module	4 Channels Single Ended, Non-Isolated Between Channel
Indicators (Logic side)	4 Green Input Status
Resolution in Ranges	14 bits: 1.22uA/Bit(0~20mA) 14 bits: 0.98uA/Bit(4~20mA) 16 bits (Include Sign) 15 bits: 0.61uA/Bit (0~20mA) 15 bits: 0.49uA/Bit*4~20mA)
Input Current Ranges	0~20mA, 4~20mA
Data Format	16 Bits Integer (2 ^l complement)
Module Error	±0.1% Full Scale @ 25°C ambient ±0.3% Full Scale @ -40°C ~ 70°C
Input Impedance	121.5 Ω
Diagnostic	Diagnostic Field Power Off: LED Blinking Field Power On: LED Off < 0.5% (Maximum Input Value) Field Power On: LED On > 0.5% (Maximum Input Value) Minimum Range Over: LED Off < 3mA (4~20mA)
Conversion Time	0.7msec / All Channels
Field Calibration	Not Required
Common Type	4 Common, Field Power 0V is the Common (AGND)
General Specification	
Power Dissipation	Max. 25mA @ 5.0Vdc
Isolation	I/O to Logic: Isolation Field Power: Non-Isolation
UL Field Power	Supply Voltage: 24Vdc nominal, Class 2
Field Power	Supply Voltage: 24Vdc nominal Voltage Range: 18~30Vdc Power Dissipation: Max. 20mA @ 24Vdc
Wiring	I/O Cable Max. 2.0mm ² (AWG 14)
Torque	0.8Nm (7lb-in)
Weight	58g
Module Size	12mm x 99mm x 70mm

3.2.6 Data Value / Current


Current Range: 0 ~ 20mA

Current	0.0mA	5.0mA	10.0mA	20.0mA
Data(Hex)	H0000	H1FFF	H3FFF	H7FFF



Current Range: 4 ~ 20mA


Current	4.0mA	8.0mA	12.0mA	20.0mA
Data(Hex)	H0000	H1FFF	H3FFF	H7FFF



3.2.7 Mapping Data into the Image Table.

Input Module Data

Analog Input Ch0
Analog Input Ch1
Analog Input Ch2
Analog Input Ch3



Input Image Value

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0					Analog Input Ch0 Low byte			
Byte 1					Analog Input Ch0 High byte			
Byte 2					Analog Input Ch1 Low byte			
Byte 3					Analog Input Ch1 High byte			
Byte 4					Analog Input Ch2 Low byte			
Byte 5					Analog Input Ch2 High byte			
Byte 6					Analog Input Ch3 Low byte			
Byte 7					Analog Input Ch3 High byte			

3.2.8 Parameter Data


Valid Parameter length: 6 Bytes

Parameter Data

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0					Current Range for Channel 0 (H00: 0~20mA, H01: 4~20mA)			
Byte 1					Current Range for Channel 1 (H00: 0~20mA, H01: 4~20mA)			
Byte 2					Current Range for Channel 2 (H00: 0~20mA, H01: 4~20mA)			
Byte 3					Current Range for Channel 3 (H00: 0~20mA, H01: 4~20mA)			
Byte 4					Filter Time (H00: Default Filter (20) / H01: Fastest ~ / H3E: Slowest)			
Byte 5					Not used (=00)			


3.3 RIO3-AX8I

3.3.1 Wiring Diagram



Pin No.	Signal Description	Signal Description	Pin No.
0	Input Channel 0	Input Channel 1	1
2	Input Channel 2	Input Channel 3	3
4	Input Channel 4	Input Channel 5	5
6	Input Channel 6	Input Channel 7	7
8	Input Channel Common (AGND)	Input Channel Common (AGND)	9

3.3.2 LED Indicator



LED No.	LED Function / Description	LED Color
0	Input Channel 0	Green
1	Input Channel 1	Green
2	Input Channel 2	Green
3	Input Channel 3	Green
4	Input Channel 4	Green
5	Input Channel 5	Green
6	Input Channel 6	Green
7	Input Channel 7	Green

3.3.3 Channel Status LED

Status	LED	To indicate
Normal Operation	OFF Green	< 0.5% (Maximum Input Value) > 0.5% (Maximum Input Value)
Overrun/Underrun	OFF	> 21mA (Maximum Range Over) < 3mA (Minimum Range Over, 4 ~ 20mA)
Field Power Error	All Channel Repeat the Green and Off	Field Power is unconnected

3.3.4 Environment Specification

Environmental Specification	
Operation Temperature	-40°C ~ 60°C
UL Temperature	-20°C ~ 60°C
Storage Temperature	-40°C ~ 85°C
Relative Humidity	5% ~ 90% non-condensing
Mounting	DIN Rail
General Specification	
Shock Operating	IEC 60068-2-27
Vibration Resistance	Based on IEC 60068-2-6, 4g
Industrial Emissions	EN61000-6-4/A11: 2011
Industrial Immunity	EN61000-6-2: 2005
Installation Position	Vertical and horizontal installation is possible
Product Certifications	CE, UL


3.3.5 Specification

Items	Specification
Input Specification	
Inputs Per Module	8 Channels Single Ended, Non-Isolated Between Channel
Indicators (Logic side)	8 Green Input Status
Resolution in Ranges	12 Bits: 4.88uA/Bit (0~20mA), 3.91uA/Bit (4~20mA)
Input Current Ranges	0 ~ 20mA, 4 ~ 20mA
Data Format	16 Bits Integer (2' complement)
Module Error	±0.1% Full Scale @ 25°C ambient ±0.3% Full Scale @ -40°C ~ 70°C
Input Impedance	121.5 Ω
Diagnostic	Diagnostic Field Power Off: LED Blinking Field Power On: LED Off < 0.5% (Maximum Input Value) Field Power On: LED On > 0.5% (Maximum Input Value) Maximum Range Over: LED Off > 21mA Minimum Range Over: LED Off < 3mA (4~20mA)
Conversion Time	1.5msec / All Channels
Field Calibration	Not Required
Common Type	2 Common, Field Power 0V is the Common (AGND)
General Specification	
Power Dissipation	Max. 30mA @ 5.0Vdc
Isolation	I/O to Logic: Isolation Field Power: Non-Isolation
UL Field Power	Supply Voltage: 24Vdc nominal, Class 2
Field Power	Supply Voltage: 24Vdc nominal Voltage Range: 18 ~ 30Vdc Power Dissipation: Max. 30mA @ 24Vdc
Wiring	I/O Cable Max. 2.0mm ² (AWG 14)
Torque	0.8Nm (7lb-in)
Weight	58g
Module Size	12mm x 99mm x 70mm
Environment Condition	Refer to 'Environment Specification'

3.3.6 Data Value / Current


Current Range: 0 ~ 20mA

Current	0.0mA	5.0mA	10.0mA	20.0mA
Data(Hex)	H0000	H03FF	H07FF	H0FFF



Current Range: 4 ~ 20mA


Current	4.0mA	8.0mA	12.0mA	20.0mA
Data(Hex)	H0000	H03FF	H07FF	H0FFF



3.3.7 Mapping Data into the Image Table.

Input Module Data

Analog Input Ch0
Analog Input Ch1
Analog Input Ch2
Analog Input Ch3
Analog Input Ch4
Analog Input Ch5
Analog Input Ch6
Analog Input Ch7



Input Image Value

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0					Analog Input Ch0 Low byte			
Byte 1					Analog Input Ch0 High byte			
Byte 2					Analog Input Ch1 Low byte			
Byte 3					Analog Input Ch1 High byte			
Byte 4					Analog Input Ch2 Low byte			
Byte 5					Analog Input Ch2 High byte			
Byte 6					Analog Input Ch3 Low byte			
Byte 7					Analog Input Ch3 High byte			
Byte 8					Analog Input Ch4 Low byte			
Byte 9					Analog Input Ch4 High byte			
Byte 10					Analog Input Ch5 Low byte			
Byte 11					Analog Input Ch5 High byte			
Byte 12					Analog Input Ch6 Low byte			
Byte 13					Analog Input Ch6 High byte			
Byte 14					Analog Input Ch7 Low byte			
Byte 15					Analog Input Ch7 High byte			

3.3.8 Parameter Data


Valid Parameter length: 10 Bytes

Parameter Data

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0								Current Range for Channel 0 (H00: 0~20mA, H01: 4~20mA)
Byte 1								Current Range for Channel 1 (H00: 0~20mA, H01: 4~20mA)
Byte 2								Current Range for Channel 2 (H00: 0~20mA, H01: 4~20mA)
Byte 3								Current Range for Channel 3 (H00: 0~20mA, H01: 4~20mA)
Byte 4								Current Range for Channel 4 (H00: 0~20mA, H01: 4~20mA)
Byte 5								Current Range for Channel 5 (H00: 0~20mA, H01: 4~20mA)
Byte 6								Current Range for Channel 6 (H00: 0~20mA, H01: 4~20mA)
Byte 7								Current Range for Channel 7 (H00: 0~20mA, H01: 4~20mA)
Byte 8								Filter Time (H00: Default Filter (20) / H01: Fastest ~ / H3E: Slowest)
Byte 9								Not used (=00)


3.4 RIO3-AXH8I

3.4.1 Wiring Diagram



Pin No.	Signal Description	Signal Description	Pin No.
0	Input Channel 0	Input Channel 1	1
2	Input Channel 2	Input Channel 3	3
4	Input Channel 4	Input Channel 5	5
6	Input Channel 6	Input Channel 7	7
8	Input Channel Common (AGND)	Input Channel Common (AGND)	9

3.4.2 LED Indicator



LED No.	LED Function / Description	LED Color
0	Input Channel 0	Green
1	Input Channel 1	Green
2	Input Channel 2	Green
3	Input Channel 3	Green
4	Input Channel 4	Green
5	Input Channel 5	Green
6	Input Channel 6	Green
7	Input Channel 7	Green

3.4.3 Channel Status LED

Status	LED	To indicate
Normal Operation	OFF Green	< 0.5% (Maximum Input Value) > 0.5% (Maximum Input Value)
Overrun/Underrun	OFF	< 3mA (Minimum Range Over, 4 ~ 20mA)
Field Power Error	All Channel Repeat the Green and Off	Field Power is unconnected

3.4.4 Environment Specification

Environmental Specification	
Operation Temperature	-40°C ~ 60°C
UL Temperature	-20°C ~ 60°C
Storage Temperature	-40°C ~ 85°C
Relative Humidity	5% ~ 90% non-condensing
Mounting	DIN Rail
General Specification	
Shock Operating	IEC 60068-2-27
Vibration Resistance	Based on IEC 60068-2-6, 4g
Industrial Emissions	EN61000-6-4/A11: 2011
Industrial Immunity	EN61000-6-2: 2005
Installation Position	Vertical and horizontal installation is possible
Product Certifications	CE, UL


3.4.5 Specification

Items	Specification
Input Specification	
Inputs Per Module	8 Channels Single Ended, Non-Isolated Between Channel
Indicators (Logic side)	8 Green Input Status
Resolution in Ranges	14 bits: 1.22uA/Bit(0~20mA) 14 bits: 0.98uA/Bit(4~20mA) 16 bits (Include Sign) 15 bits: 0.61uA/Bit (0~20mA) 15 bits: 0.49uA/Bit(4~20mA)
Input Current Ranges	0 ~ 20mA, 4 ~ 20mA
Data Format	16 Bits Integer (2 ^l complement)
Module Error	±0.1% Full Scale @ 25°C ambient ±0.3% Full Scale @ -40°C ~ 70°C
Input Impedance	121.5 Ω
Diagnostic	Diagnostic Field Power Off: LED Blinking Field Power On: LED Off < 0.5% (Maximum Input Value) Field Power On: LED On > 0.5% (Maximum Input Value) Minimum Range Over: LED Off < 3mA (4~20mA)
Conversion Time	1.5msec / All Channels
Field Calibration	Not Required
Common Type	2 Common, Field Power 0V is the Common (AGND)
General Specification	
Power Dissipation	Max. 30mA @ 5.0Vdc
Isolation	I/O to Logic: Isolation Field Power: Non-Isolation
UL Field Power	Supply Voltage: 24Vdc nominal, Class 2
Field Power	Supply Voltage: 24Vdc nominal Voltage Range: 18~30Vdc Power Dissipation: Max. 25mA @ 24Vdc
Wiring	I/O Cable Max. 2.0mm ² (AWG 14)
Torque	0.8Nm (7lb-in)
Weight	58g
Module Size	12mm x 99mm x 70mm

3.4.6 Data Value / Current


Current Range: 0 ~ 20mA

Current	0.0mA	5.0mA	10.0mA	20.0mA
Data(Hex)	H0000	H1FFF	H3FFF	H7FFF



Current Range: 4 ~ 20mA


Current	4.0mA	8.0mA	12.0mA	20.0mA
Data(Hex)	H0000	H1FFF	H3FFF	H7FFF



3.4.7 Mapping Data into the Image Table.

Input Module Data

Analog Input Ch0
Analog Input Ch1
Analog Input Ch2
Analog Input Ch3
Analog Input Ch4
Analog Input Ch5
Analog Input Ch6
Analog Input Ch7



Input Image Value

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0					Analog Input Ch0 Low byte			
Byte 1					Analog Input Ch0 High byte			
Byte 2					Analog Input Ch1 Low byte			
Byte 3					Analog Input Ch1 High byte			
Byte 4					Analog Input Ch2 Low byte			
Byte 5					Analog Input Ch2 High byte			
Byte 6					Analog Input Ch3 Low byte			
Byte 7					Analog Input Ch3 High byte			
Byte 8					Analog Input Ch4 Low byte			
Byte 9					Analog Input Ch4 High byte			
Byte 10					Analog Input Ch5 Low byte			
Byte 11					Analog Input Ch5 High byte			
Byte 12					Analog Input Ch6 Low byte			
Byte 13					Analog Input Ch6 High byte			
Byte 14					Analog Input Ch7 Low byte			
Byte 15					Analog Input Ch7 High byte			

3.4.8 Parameter Data


Valid Parameter length: 10 Bytes

Parameter Data

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0								Current Range for Channel 0 (H00: 0~20mA, H01: 4~20mA)
Byte 1								Current Range for Channel 1 (H00: 0~20mA, H01: 4~20mA)
Byte 2								Current Range for Channel 2 (H00: 0~20mA, H01: 4~20mA)
Byte 3								Current Range for Channel 3 (H00: 0~20mA, H01: 4~20mA)
Byte 4								Current Range for Channel 4 (H00: 0~20mA, H01: 4~20mA)
Byte 5								Current Range for Channel 5 (H00: 0~20mA, H01: 4~20mA)
Byte 6								Current Range for Channel 6 (H00: 0~20mA, H01: 4~20mA)
Byte 7								Current Range for Channel 7 (H00: 0~20mA, H01: 4~20mA)
Byte 8								Filter Time (H00: Default Filter (20) / H01: Fastest ~ / H3E: Slowest)
Byte 9								Not used (=00)


3.5 RIO3-AX16IC

3.5.1 Wiring Diagram



Pin No.	Signal Description	Signal Description	Pin No.
0	Input Channel 0	Input Channel 1	1
2	Input Channel 2	Input Channel 3	3
4	Input Channel 4	Input Channel 5	5
6	Input Channel 6	Input Channel 7	7
8	Input Channel 8	Input Channel 9	9
10	Input Channel 10	Input Channel 11	11
12	Input Channel 12	Input Channel 13	13
14	Input Channel 14	Input Channel 15	15
16	Input Channel Common (AGND)	Input Channel Common (AGND)	17
18	Input Channel Common (AGND)	Input Channel Common (AGND)	19

3.5.2 LED Indicator



LED No.	LED Function / Description	LED Color
0	Status LED	Green

3.5.3 Channel Status LED

Status	LED	To indicate
G-Bus Status	Off Green	Disconnection Connection
Field Power Error	All Channel Repeat the Green and Off	Field Power is unconnected

3.5.4 Environment Specification

Environmental Specification	
Operation Temperature	-40°C ~ 60°C
UL Temperature	-20°C ~ 60°C
Storage Temperature	-40°C ~ 85°C
Relative Humidity	5% ~ 90% non-condensing
Mounting	DIN Rail
General Specification	
Shock Operating	IEC 60068-2-27
Vibration Resistance	Based on IEC 60068-2-6, 4g
Industrial Emissions	EN61000-6-4/A11: 2011
Industrial Immunity	EN61000-6-2: 2005
Installation Position	Vertical and horizontal installation is possible
Product Certifications	CE, UL


3.5.5 Specification

Items	Specification
Input Specification	
Inputs Per Module	16 Channels Single Ended, Non-Isolated Between Channel
Indicators (Logic side)	1 Green Input Status
Resolution in Ranges	12 Bits: 4.88uA/Bit (0~20mA), 3.91uA/Bit (4~20mA)
Input Current Ranges	0 ~ 20mA, 4 ~ 20mA
Data Format	16 Bits Integer (2 ^l compliment)
Module Error	±0.1% Full Scale @ 25°C ambient ±0.3% Full Scale @ -40°C ~ 60°C
Input Impedance	121.5 Ω
Diagnostic	Diagnostic Field Power Off: LED Blinking
Conversion Time	1.2msec / All Channels
Field Calibration	Not Required
Common Type	4 Common, Field Power 0V is the Common (AGND)
General Specification	
Power Dissipation	Max. 30mA @ 5.0Vdc
Isolation	I/O to Logic: Isolation Field Power: Non-Isolation
UL Field Power	Supply Voltage: 24Vdc nominal, Class 2
Field Power	Supply Voltage: 24Vdc nominal Voltage Range: 18 ~ 26.4Vdc Power Dissipation: Max. 35mA @ 24Vdc
Wiring	Connector Type, up to AWG22 Module connector: HIF3BA-20D-2.54DSA
Weight	58g
Module Size	12mm x 99mm x 70mm

3.5.6 Data Value / Current


Current Range: 0 ~ 20mA

Current	0.0mA	5.0mA	10.0mA	20.0mA
Data(Hex)	H0000	H03FF	H07FF	H0FFF



Current Range: 4 ~ 20mA


Current	4.0mA	8.0mA	12.0mA	20.0mA
Data(Hex)	H0000	H03FF	H07FF	H0FFF



3.5.7 Mapping Data into the Image Table.

Input Module Data

Analog Input Ch0
Analog Input Ch1
Analog Input Ch2
Analog Input Ch3
Analog Input Ch4
Analog Input Ch5
Analog Input Ch6
Analog Input Ch7
Analog Input Ch8
Analog Input Ch9
Analog Input Ch10
Analog Input Ch11
Analog Input Ch12
Analog Input Ch13
Analog Input Ch14
Analog Input Ch15



Input Image Value

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0					Analog Input Ch0 Low byte			
Byte 1					Analog Input Ch0 High byte			
Byte 2					Analog Input Ch1 Low byte			
Byte 3					Analog Input Ch1 High byte			
Byte 4					Analog Input Ch2 Low byte			
Byte 5					Analog Input Ch2 High byte			
Byte 6					Analog Input Ch3 Low byte			
Byte 7					Analog Input Ch3 High byte			
Byte 8					Analog Input Ch4 Low byte			
Byte 9					Analog Input Ch4 High byte			
Byte 10					Analog Input Ch5 Low byte			
Byte 11					Analog Input Ch5 High byte			
Byte 12					Analog Input Ch6 Low byte			
Byte 13					Analog Input Ch6 High byte			
Byte 14					Analog Input Ch7 Low byte			
Byte 15					Analog Input Ch7 High byte			
Byte 16					Analog Input Ch8 Low byte			
Byte 17					Analog Input Ch8 High byte			
Byte 18					Analog Input Ch9 Low byte			

Byte 19	Analog Input Ch9 High byte
Byte 20	Analog Input Ch10 Low byte
Byte 21	Analog Input Ch10 High byte
Byte 22	Analog Input Ch11 Low byte
Byte 23	Analog Input Ch11 High byte
Byte 24	Analog Input Ch12 Low byte
Byte 25	Analog Input Ch12 High byte
Byte 26	Analog Input Ch13 Low byte
Byte 27	Analog Input Ch13 High byte
Byte 28	Analog Input Ch14 Low byte
Byte 29	Analog Input Ch14 High byte
Byte 30	Analog Input Ch15 Low byte
Byte 31	Analog Input Ch15 High byte

3.5.8 Parameter Data


Valid Parameter length: 18 Bytes

Parameter Data

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0								Current Range for Channel 0 (H00: 0~20mA, H01: 4~20mA)
Byte 1								Current Range for Channel 1 (H00: 0~20mA, H01: 4~20mA)
Byte 2								Current Range for Channel 2 (H00: 0~20mA, H01: 4~20mA)
Byte 3								Current Range for Channel 3 (H00: 0~20mA, H01: 4~20mA)
Byte 4								Current Range for Channel 4 (H00: 0~20mA, H01: 4~20mA)
Byte 5								Current Range for Channel 5 (H00: 0~20mA, H01: 4~20mA)
Byte 6								Current Range for Channel 6 (H00: 0~20mA, H01: 4~20mA)
Byte 7								Current Range for Channel 7 (H00: 0~20mA, H01: 4~20mA)
Byte 8								Current Range for Channel 8 (H00: 0~20mA, H01: 4~20mA)
Byte 9								Current Range for Channel 9 (H00: 0~20mA, H01: 4~20mA)
Byte 10								Current Range for Channel 10 (H00: 0~20mA, H01: 4~20mA)
Byte 11								Current Range for Channel 11 (H00: 0~20mA, H01: 4~20mA)
Byte 12								Current Range for Channel 12 (H00: 0~20mA, H01: 4~20mA)
Byte 13								Current Range for Channel 13 (H00: 0~20mA, H01: 4~20mA)
Byte 14								Current Range for Channel 14 (H00: 0~20mA, H01: 4~20mA)
Byte 15								Current Range for Channel 15 (H00: 0~20mA, H01: 4~20mA)
Byte 16								Filter Time (H00: Default Filter (20) / H01: Fastest ~ / H3E: Slowest)
Byte 17								Not used (=00)


3.6 RIO3-AX16IT

3.6.1 Wiring Diagram



Pin No.	Signal Description
0	Input Channel 0
1	Input Channel 1
2	Input Channel 2
3	Input Channel 3
4	Input Channel 4
5	Input Channel 5
6	Input Channel 6
7	Input Channel 7
8	Input Channel 8
9	Input Channel 9
10	Input Channel 10
11	Input Channel 11
12	Input Channel 12
13	Input Channel 13
14	Input Channel 14
15	Input Channel 15
16	Input Channel Common (AGND)
17	Input Channel Common (AGND)

3.6.2 LED Indicator



LED No.	LED Function / Description	LED Color
0	Status LED	Green

3.6.3 Channel Status LED

Status	LED	To indicate
G-Bus Status	Off Green	Disconnection Connection

3.6.4 Environment Specification

Environmental Specification	
Operation Temperature	-40°C ~ 60°C
UL Temperature	-20°C ~ 60°C
Storage Temperature	-40°C ~ 85°C
Relative Humidity	5% ~ 90% non-condensing
Mounting	DIN Rail
General Specification	
Shock Operating	IEC 60068-2-27
Vibration Resistance	Based on IEC 60068-2-6, 4g
Industrial Emissions	EN 61000-6-4/A11: 2011
Industrial Immunity	EN 61000-6-2: 2005
Installation Position	Vertical and horizontal installation is available
Product Certifications	CE, UL


3.6.5 Specification

Items	Specification
Input Specification	
Inputs Per Module	16 Channels Single Ended, Non-Isolated Between Channel
Indicators (Logic side)	1 Green Input Status
Resolution in Ranges	12 Bit: 4.88uA / Bit (0~20mA), 3.91uA / Bit (4~20mA)
Input Current Ranges	0~20mA, 4~20mA
Data Format	16 Bits Integer (2' complement)
Module Error	±0.1% Full Scale @ 25°C ambient ±0.3% Full Scale @ -40°C ~ 60°C
Input Impedance	121.5 Ω
Conversion Time	1.2msec / All Channels
Field Calibration	Not Required
Common Type	2 Common, Field Power 0V is the Common (AGND)
General Specification	
Power Dissipation	Max. 200mA @ 5.0Vdc
Isolation	I/O to Logic: Isolation Field Power: Non-Isolation
UL Field Power	Supply Voltage: 24Vdc nominal, Class 2
Field Power	Not used Field Power bypass to next expansion module
Single Wiring	I/O Cable Max. 1.0mm ² (AWG18)
Weight	63g
Module Size	12mm x 109mm x 70mm

3.6.6. Data Value / Current


Current Range: 0 ~ 20mA

Current	0.0mA	5.0mA	10.0mA	20.0mA
Data(Hex)	H0000	H03FF	H07FF	H0FFF



Current Range: 4 ~ 20mA


Current	4.0mA	8.0mA	12.0mA	20.0mA
Data(Hex)	H0000	H03FF	H07FF	H0FFF



3.6.7. Mapping Data into the Image Table.

Input Module Data

Analog Input Ch0
Analog Input Ch1
Analog Input Ch2
Analog Input Ch3
Analog Input Ch4
Analog Input Ch5
Analog Input Ch6
Analog Input Ch7
Analog Input Ch8
Analog Input Ch9
Analog Input Ch10
Analog Input Ch11
Analog Input Ch12
Analog Input Ch13
Analog Input Ch14
Analog Input Ch15



Input Image Value

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0					Analog Input Ch0 Low byte			
Byte 1					Analog Input Ch0 High byte			
Byte 2					Analog Input Ch1 Low byte			
Byte 3					Analog Input Ch1 High byte			
Byte 4					Analog Input Ch2 Low byte			
Byte 5					Analog Input Ch2 High byte			
Byte 6					Analog Input Ch3 Low byte			
Byte 7					Analog Input Ch3 High byte			
Byte 8					Analog Input Ch4 Low byte			
Byte 9					Analog Input Ch4 High byte			
Byte 10					Analog Input Ch5 Low byte			
Byte 11					Analog Input Ch5 High byte			
Byte 12					Analog Input Ch6 Low byte			
Byte 13					Analog Input Ch6 High byte			
Byte 14					Analog Input Ch7 Low byte			
Byte 15					Analog Input Ch7 High byte			
Byte 16					Analog Input Ch8 Low byte			
Byte 17					Analog Input Ch8 High byte			
Byte 18					Analog Input Ch9 Low byte			

Byte 19	Analog Input Ch9 High byte
Byte 20	Analog Input Ch10 Low byte
Byte 21	Analog Input Ch10 High byte
Byte 22	Analog Input Ch11 Low byte
Byte 23	Analog Input Ch11 High byte
Byte 24	Analog Input Ch12 Low byte
Byte 25	Analog Input Ch12 High byte
Byte 26	Analog Input Ch13 Low byte
Byte 27	Analog Input Ch13 High byte
Byte 28	Analog Input Ch14 Low byte
Byte 29	Analog Input Ch14 High byte
Byte 30	Analog Input Ch15 Low byte
Byte 31	Analog Input Ch15 High byte

3.6.8. Parameter Data


Valid Parameter length: 18 Bytes

Parameter Data

Bit No	Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Byte 0								Current Range for Channel 0 (H00: 0~20mA, H01: 4~20mA)
Byte 1								Current Range for Channel 1 (H00: 0~20mA, H01: 4~20mA)
Byte 2								Current Range for Channel 2 (H00: 0~20mA, H01: 4~20mA)
Byte 3								Current Range for Channel 3 (H00: 0~20mA, H01: 4~20mA)
Byte 4								Current Range for Channel 4 (H00: 0~20mA, H01: 4~20mA)
Byte 5								Current Range for Channel 5 (H00: 0~20mA, H01: 4~20mA)
Byte 6								Current Range for Channel 6 (H00: 0~20mA, H01: 4~20mA)
Byte 7								Current Range for Channel 7 (H00: 0~20mA, H01: 4~20mA)
Byte 8								Current Range for Channel 8 (H00: 0~20mA, H01: 4~20mA)
Byte 9								Current Range for Channel 9 (H00: 0~20mA, H01: 4~20mA)
Byte 10								Current Range for Channel 10 (H00: 0~20mA, H01: 4~20mA)
Byte 11								Current Range for Channel 11 (H00: 0~20mA, H01: 4~20mA)
Byte 12								Current Range for Channel 12 (H00: 0~20mA, H01: 4~20mA)
Byte 13								Current Range for Channel 13 (H00: 0~20mA, H01: 4~20mA)
Byte 14								Current Range for Channel 14 (H00: 0~20mA, H01: 4~20mA)
Byte 15								Current Range for Channel 15 (H00: 0~20mA, H01: 4~20mA)
Byte 16								Filter Time (H00: Default Filter (20) / H01: Fastest ~ / H3E: Slowest)
Byte 17								Not used (=00)





4. Dimension

4.1. 10-Pts. Spring Type




Dimensions in mm

4.2. 20-Pin Connector Type



Measurements in mm

4.3. 18-Pts. Spring Type



Measurements in mm

5. Mounting

Caution!

Hot surface!


The surface of the housing can become hot during operation. If the device was operated at high ambient temperatures, allow it to be cool before touching it.

Notice!

Perform work on devices only if they are de-energized!

Working on energized devices can damage them. Therefore, turn off the power supply before working on the devices.


5.1. I/O Inserting and Removing Devices



As above figure in order to safeguard the RIO3-Series module from jamming, it should be fixed onto the DIN rail with locking lever. To do so, fold on the upper of the locking lever.

To pull out the RIO3-Series module, unfold the locking lever as below figure.

5.2. RTB (Removable Terminal Block)



Whole terminal block can be combined and removed for the convenience.

There is a locking switch on the RTB for the easy combination and easy removal.

Easy combination and easy removal for I/O modules on the DIN rail through One Touch Locking Switch.

6. G-Bus Pin Description

Communication between the Network Adapter and the expansion module as well as system / field power supply of the bus modules is carried out via the internal bus. It is comprised of 6 data pin and 2 field power pin.



*Please refer to the table below regarding the pin description from P1 to P8.

No.	Description
P1	System Power (VCC)
P2	System Power (GND)
P3	GBUS TX +
P4	GBUS TX -
P5	GBUS RX +
P6	GBUS RX -
P7	Field Power (GND)
P8	Field Power (VCC)

DANGER



Do not touch data and field power pins in order to avoid soiling and damage by ESD noise.

APPENDIX A

A.1. Product List

Please refer the separate HX-RIO3 product list document

A.2. Glossary

System Power: The power for starting up CPU.

Field Power: The power for input and output line.

Terminator Resistor: Resistor for prevention reflected wave.

EDS: Electronic Data Sheet.

Sink: The method of in/output power supply if a device has no power source.

Source: The method of in/output power supply if a device has the power source.