
## CA-EPuni2 RS232, eSMART107 RS232 - open wires


Date: March 1st, 2018

Revision: 02 Auteur: ES

Cable code	CA-EPuni2 RS232		
Hiflex article number			
Description	Exor eSMART107 X4 connector, (COM1 & COM4)		
	Standard cable length 3 meters		
Type of Communication	RS232		
Cable connector, panel side	Molex connector		
Device Connector	Open wires		
Notes	Communication lines are shielded		



## RS232 (ref. X4)



Reference	Pin	Description	
	1	GND	
X4	2	TxD	
RS232	3	RxD	
(COM1)	4	RTS	
	5	CTS	
	6	GND:	
X4	7	TxD	
RS232	8	RxD	
(COM4)	9	RTS	
	10	CTS	

## **Molex connector:**

For assembly of the Molex connector special tools and parts are needed.

Item	Molex PN	Description
Molex tools,	63819-0000	Hand crimp tool, ratchet + locator assembly
needed for connector	63819-0075	Spare, locator assembly (optional)
assembly panel side	11-03-0043	Extraction tool, micro fit (optional)
Panel X2 and X3	43025-1208	12 way connector housing
serial ports (RS485 + CAN)	43030-0001	Contact, Micro-Fit 3.0
Panel X4	43025-1000	10 way connector housing
serial port (2x RS232)	43030-0001	Contact, Micro-Fit 3.0

The schematics in this document are drawn as accurate as possible. Most cables are tested and approved. However there are still possibilities of errors. Hiflex strongly recommends that cables are tested before use in practice. Hiflex will not be held responsible for possible errors in this document.

